

Manufacturer Declaration Functional Safety (IEC 61508:2010)

Supplement 1 / NE130 From B.1

Endress+Hauser Wetzer GmbH+Co. KG Obere Wank 1, 87484 Nesselwang

declares as manufacturer, that the following surge protective device

HAW566

is suitable for use in safety relevant applications up to SIL3 (HFT=0) according to IEC 61508:2010

In safety relevant applications according to IEC 61508, the instructions of the Safety Manual must be followed.

Nesselwang, 24.4.2025 Endress+Hauser Wetzer GmbH+Co. KG

ppa. Harald Müller Director Technology

i.V. Eva Rizzo Head of Department Technology Safety

Endress+Hauser

People for Process Automation

General						
Device designation and permissible types		HAW566 (Order code for "Additional approval ": Option LA "SIL")				
Safety-related output signal		n/a				
Fault current		n/a				
Process variable/function		Provide surge protection for field equipment				
Safety function(s)		The safety function of Surge Protective Devices is to behave like a piece of copper wire, passing through the process signal without being altered.				
Device type acc. to IEC 61508-2		🗹 Туре А 🛛		🗖 Туре В	/pe B	
Operating mode	ä	☑ Low Demand Mod		☑ High Demand	Continuous Mode	
Valid Hardware-Ve	ersion	n/a				
Valid Software-Version		n/a				
Safety manual		FY01110K/09				
Type of evaluation (check only <u>one</u> box)		Complete HW/SW evaluation parallel to development incl. FMEDA and change request acc. to IEC 61508-2, 3				
		Evaluation of "Proven-in-use" performance for HW/SW incl. FMEDA and change request acc. to IEC 61508-2, 3				
			IEC 61511			
		Evaluation by FMEA acc. to IEC61508-2 for devices in respect of hardwar safety integrity				
Evaluation through / certificate no.		internal assessment				
Test documents		deve	elopment documents, t	est reports, data sheets		
SIL - Integri	ty					
Systematic safety integrity				SIL 2 capal	ble 🗹 SIL 3 capable	
Hardware safety integrity		2-wire signal use (HFT = 0)			ble 🗹 SIL 3 capable	
		3-wire signal use (HFT = 0)) 🛛 🗖 SIL 2 capał	ole 🗹 SIL 3 capable	
		2-wi	re power use (HFT = 0) SIL 2 capat	ole 🗹 SIL 3 capable	
FMEA			HAW566			
Safety function		The safety function of a Surge Protective Devices is to behave like a piece of copper wire, passing through the process signal without being altered.				
λ _{DU} ^{1) 2)}		1.71E-09 (2-wire signal), 2.57E-09 (3-wire signal), 0 (2-wire power)				
λ _{DD} ^{1) 2)}		1.68E-08 (2-wire signal), 2.48E-08 (3-wire signal), 0 (2-wire power)				
λ _{SU} ^{1) 2)}		5.37E-08 (2-wire signal), 6.05E-08 (3-wire signal), 0 (2-wire power)				
SFF - Safe Failure Fraction		97.63% (2-wire signal), 97.44% (3-wire signal)				
$PFD_{avg} \ T_1 = 4 \ year^{\ 2)}$		0 .00 (2-wire power)				
$PFD_{avg} T_1 = 20 \text{ years }^{2)}$		3.76E-05 (2-wire signal), 5.64E-05 (3-wire signal)				
PFH		n/a				
PTC ³⁾		n/a				
Fault reaction time ⁴⁾		n/a				
Diagnostic test interval 5)		n/a				
Process safety time 6)		n/a				
MTTF 7)	-		n/a	· · · · · · · · · · · · · · · · · · ·		
Declaration						
		rnal company quality management system ensures information on safety-related systematic faults which evident in the future				

¹⁾ FIT = Failure In Time, Number of failures per 10^9 h

²⁾ Valid for average ambient temperature up to +80 °C (+176 °F)

For continuous operation at ambient temperature close to +80 °C (+176 °F), a factor of 2 should be applied

³⁾ PTC = Proof Test Coverage

⁴⁾ Maximum time between error recognition and error response

⁵⁾ All online diagnostic functions are performed at least once within the Diagnostic test interval (32 min incl. memory test)

⁶⁾ The Process safety time is: Diagnostic test interval x 100 (calculated acc. to IEC 61508)

⁷⁾ MTTF (Mean Time To Failure) is the predicted elapsed time between inherent failures of a system during operation

in accordance to Siemens SN29500